

## Affordable Wi-Fi Laser Multi-Function.

Now print from your • Mobile • Tablet • Laptop.

















## DCP-1616NW Mono Laser Multi-Function Centre



General	
Function	Print   Scan   Copy
	Hi-Speed USB 2.0
Connectivity	10Base-T/100Base-TX,
	IEEE 802.11b/g/n (Infrastructure Mode/Ad-hoc Mode)
Mobile Print	Brother iPrint&Scan
Control Panel	16 characters x 2 lines
Memory	32MB
Toner Save Mode	Save toner by printing documents in toner save mode
Print Function	
Print Speed A4	Up to 20ppm
Print Resolution	Up to 2400 x 600 dpi (HQ1200 technology)
First Print Out Time (From ready mode)	<10 secs
Warm-up time (From sleep mode)	<18 secs
Copy Function	
Copy Speed	Up to 20cpm
Copy Resolution	600 x 600 dpi
First copy out time	<16 secs
Multi-Copy	Yes (Up to 99)
N-in-1 Copying	Allows the user to compress 2 or 4 pages onto a single A4 sheet
Scan Function	Scanner glass: Up to 600 x 1,200 dpi
Scan Resolution	Enhanced: Up to 19,200 x 19,200 dpi
ocan riesolation	ADF: Up to 600 x 600 dpi
Scan Functions	Enables users to scan documents to E-mail, Image, File and Sharepoint**
Media Specifications	The state of the s
•	Standard paper tray - Plain paper, recycled paper
Media Types	ADF (Automatic Document Feeder) - Plain paper, recycled paper
Media Capacity	150-sheet standard paper tray, 10-sheet ADF (Automatic Document Feeder)
Media Sizes	Standard tray - A4, Letter, Legal, Folio, A5, A5 (Long Edge), B5, Executive ADF - A4, Letter, Legal Folio
Paper Output	50-sheet
Supplies	
Inbox Toner	1,500 pages*
Standard Yield Toner	TN-1020: 1,500 pages*
Other Supplies	Drum (DR-1020) Up to 10,000 A4 pages^
Supported Operating System	
Windows	Windows XP Professional x64 Edition, Windows XP Professional, Windows XP Home Edition Windows 8.1, Windows 8, Windows 7, Windows Vista, Windows Server 2012, Windows Server 2012 R2, Windows Server 2008, Windows Server 2008 R2, Windows Server 2003, Windows Ser2003 x64 Edition.
Macintosh	OS X v10.7.5, 10.8.x, 10.9.x (Download Only)
Linux***	CUPS, LPD/LPRng (x86/x64 environment)
Network Utilities & Solutions	
BRAdmin Professional/ Light	For LAN/WAN management of your printer fleet
Web Based Management	Web browser print server management
P filter	IP address based access restriction (lpv4 only)
Dimensions (WxDxH)	
With Carton	481 x 436 x 425mm/10.1kg
Without Carton	385 x 340 x 283mm/8.2kg
Environment	
Power Consumption	Ready: 50W, Printing: 390W, Deep Sleep: 1.0W
Noise Level	52dBA (Printing)

## For Service Support

Online: Log on to www.brother.in/customercare | Email: Write to us at customercare@brother.in Dial Toll Free No.: 1-800-222-422 (For MTNL and BSNL users), 1-800-209-8904 (For Others and all Mobiles) Operating Hours: Monday to Friday (8.30 am to 5.30 pm), Saturday (9.00 am to 4.00 pm), Closed on Sundays and Public Holidays. Copyright Brother International Corporation, Japan. All Rights Reserved.